# GeO<sub>2</sub>/Ge/r-GO hybrid-composite anodes for LIBs: Effect of Ge loading on Performance

كلية الآداب والعلوم College of Arts and Sciences عامعة قطرQATAR UNIVERSITY

Christian Randell Arro, Assem Mohamed, Nasr Bensalah\*

Department of Chemistry and Earth Sciences, College of Arts and Sciences, Qatar University, P.O. Box 2713, Doha, Qatar (Correspondence: nasr.Bensalah@qu.edu.qa)

**Graduate Students, Energy and Environment** 


#### **Abstract**

Hybrid composites between Germanium (Ge) and carbonaceous materials are promising anode materials for Li-ion batteries (LIBs). The mitigation of reduced cycling ability and rate capability allows for the unhindered benefit of higher capacities in Ge-based anodes. Here, the effect of Ge mass loading on the electrochemical performance of GeO2/Ge/r-GO composites were evaluated as LIBs anode. GeO2/Ge/r-GO composites were synthesized by controlled microwave radiation of ball-milled Ge and sonicated dispersion of graphene oxide (GO). The composite anode at Ge 25% showed greatest cycling retention with 91% after 100 cycles and an average specific capacity of 300 mAh/g (1600 mAh/g Ge). At 75% Ge mass loading the anode suffered with limited cycling retention of 57.5% at the cost of greater specific capacities. The composite at 50% Ge attained advantageous characteristics of both composites with a stable cycling performance of 71.4% after 50 cycles and an average specific capacity of 400 mAh/g (1067 mAh/g Ge. These findings can be used to shape high energy Gebased anodes and guide future development in energy storage.

# Background

- Ge and carbonaceous materials have been extensively studied due to the carbonaceous' component's ability to mitigate the intrinsic problems of to Ge-based anodes
- The mitigation of reduced cycling ability and rate capability allows for the unhindered benefit of higher capacities in Ge-carbonaceous composite anodes
- Ge holds the advantage over Si in certain aspects such as electrical conductivity and lithium diffusivity

# **Experimental**




#### **Cell Fabrication**

**Half-cells** were made in **CR-2032-coin cells** within a glove box environment ( $O_2$  &  $H_2O$  < 0.1 ppm). **Super P, PVDF & NMP** were used with active material-carbon-binder ratio of 0.8 : 0.15 : 0.05 with **LiTFSI** 

Spring
Metal Disk

GeO<sub>2</sub>/Ge/r-GO Anode
Separator
Li-Metal Cathode
Positive Case




#### • Electrochemical Testing and Post-Mortem Characterization


Half-cells were subjected to **cyclic voltammetry** at 0.01 mV/s from 0.05 V to 1.5 V vs. Li<sup>+</sup>/Li followed by **GCD** and **rate capability** tests. Cells were further examined under **XPS**, **XRD**, **SEM & TEM** at 3 stages; **Electrode-slurry form (ESF)**, **Post-discharge (PD) to 0.05 V vs. Li<sup>+</sup>/Li and** Post-charge (PC) to 1.2 V vs. Li<sup>+</sup>/Li.


#### **Results and Discussion**

**Increased Ge Mass Loading** 




**SEM** showed the formation of Ge-cubes after ball-milling treatment with average size of 0.8 to 1.2  $\mu m$ . Increased Ge mass loading lead to greater surface distribution of Ge cubes above the r-GO sheets.






**XRD** depicts phase-confirmation for Ge and GeO<sub>2</sub> species whilst **Raman** confirmed reduction of GO to r-GO.



Three wt.% compared in CV and GCD tests. CV showed peak development and transitioning with increased wt.%. GCD tests show increased initial charge and discharge values with decreased cycling retention with increased wt.%.




Slurry additives add to texture messiness in Post-Mortem SEM.

SEM shows increased size of Ge cubes, as well as cracking & melding.

**TEM** likewise shows **increased size** from ESF to Post GCD stages.

Post-Mortem XPS at Ge 3d and Li 1s spectra. Key Ge 3d bonds found for Ge<sub>0</sub> and Ge-O. Binding energy shifts to lower energy at PC/PD stages hints at formation of Li<sub>x</sub>Ge alloys. Similarly, Li 1s spectra shows key bonds and a possible Li-Ge bond form at PC/PD stages.



## Conclusion

GeO<sub>2</sub>/Ge/r-GO composites were synthesized by using a controlled microwave irradiation of ball-milled Ge and sonicated dispersion of GO. Electrochemical characterization of anodes hints at the mechanism changes of lithiation/delithiation with respect to increase Ge loading shifting from Li<sup>+</sup> intercalation/de-intercalation with the r-GO framework to Ge alloy/de-alloying. Ge-based anodes can be a promising alternative to convential anodes for LIBs with higher energy density.

### Acknowledgements

This work was funded by a grant from the **Qatar University** under its collaborative grant number **QUCG-CAS-20/21-4**. Acknowledgement is also credited to **Central Laboratories Unit (CLU)** and **Center for Advanced Materials (CAM)** for the analysis.

# References

W. Li, X. Sun, Y. Yu, Si-, Ge-, Sn-Based Anode Materials for Lithium-Ion Batteries: From Structure Design to Electrochemical Performance, Small Methods. 1 (2017) 22–30. https://doi.org/10.1002/smtd.201600037.

J.-H. Koo, S.-M. Paek, Microwave-Assisted Synthesis of Ge/GeO2-Reduced Graphene Oxide Nanocomposite with Enhanced Discharge Capacity for Lithium-Ion Batteries, Nanomaterials. 11 (2021) 319. https://doi.org/10.3390/nano11020319.